

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
28 August 2003 (28.08.2003)

PCT

(10) International Publication Number
WO 03/071681 A1

(51) International Patent Classification⁷: **H03K 19/003**,
3/037, 5/15, G06F 1/10

(21) International Application Number: PCT/IB03/00282

(22) International Filing Date: 27 January 2003 (27.01.2003)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
02075705.0 21 February 2002 (21.02.2002) EP

(71) Applicant (for all designated States except US): **KONINKLIJKE PHILIPS ELECTRONICS N.V.** [NL/NL];
Groenewoudseweg 1, NL-5621 BA Eindhoven (NL).

(72) Inventor; and

(75) Inventor/Applicant (for US only): **VAN LAMMEREN, Johannes, P., M.** [NL/NL]; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).

(74) Agent: **STEENBEEK, Leonardus, J.**; Internationaal Octrooibureau B.V., Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).

(81) Designated States (national): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, OM, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.


(84) Designated States (regional): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:

— with international search report

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: INTEGRATED CIRCUIT HAVING REDUCED SUBSTRATE BOUNCE



(57) Abstract: A clock strategy is provided for digital circuits inside mixed-signal ICs. An integrated circuit in accordance with the present invention comprises a plurality of pairs of latches (L1, L2) being respectively clocked by two non-overlapping clock signals (F1, F2). The clock strategy is aimed at keeping the substrate bounce caused by the digital circuits as low as possible. Preferably, not all latches are clocked at the same time, but delays are inserted in the clock lines so that the various latches do not consume current all at the same time. The invention relaxes the demands on the substrate sensitivity of the analog circuits.

INTEGRATED CIRCUIT HAVING REDUCED SUBSTRATE BOUNCE

The invention relates to integrated circuits and, more specifically, to a reduction of substrate bounce in digital circuits.

One of the major problems of digital circuits is the substrate bounce that they
5 cause. The substrate bounce is a great obstacle when integrating analog circuits in the same IC. But, with the ever increasing speed of digital processes, the currents in the digital circuits have become so high that they even start to affect the local supply (and hence the performance) of the digital circuits themselves.

10 It is, inter alia, an object of the invention to provide improved integrated circuits. To this end, the invention provides an integrated circuit as defined in the independent claim. Advantageous embodiments are defined in the dependent claims.

These and other aspects of the invention will be apparent from and elucidated with reference to the embodiments described hereinafter.

15

In the drawings:

Fig. 1 shows a prior art clock tree;

Fig. 2 shows a prior art edge-triggered flip-flop having two latches;

20 Fig. 3 shows an embodiment of a flip-flop having two latches clocked in accordance with the present invention with two non-overlapping clock phases;

Fig. 4 shows an embodiment of a clock line for non-simultaneous switching of the latches of one of the two clock phases; and

Fig. 5 shows an embodiment of a clock line in which each buffer drives more than one latch.

25

In many applications, e.g. microprocessors and memories, the maximum speed is absolutely crucial. No compromises on top speed are acceptable if you want to be on the cutting edge in those fields. But there are also fields, e.g. one-chip processors for analog broadcast TV, where top speed of digital circuits is not the number one priority. But, if the

digital circuits are not running at their maximum speed to perform their function, this implies they are idling part of the time. This is a waste of resources. The invention is based on the recognition that this time can be used to solve the substrate bounce problem. And, if there is time to spare, in a preferred embodiment of the present invention another highly annoying
5 problem of fast digital circuits is tackled as well: clock skew.

Fast digital circuits usually have a synchronous clock strategy. This means that all flip-flops in the circuit are supposed to switch simultaneously. Using one clock buffer to drive the load of all flip-flops in the circuit is not practical. So, instead of one clock buffer a
10 clock tree is used, as shown in Fig. 1. The clock tree of Fig. 1 has a plurality of buffers B between a clock in C_i and a clock out C_o . The clock tree has to be designed in such a way that all buffers B that are connected to flip-flops switch at the same time. This clock strategy has the advantage that the circuits can be extremely fast, but as all flip-flops switch simultaneously, the switching currents are very large. This causes both substrate bounce and
15 momentary drops of the supply voltage (which slows the circuit down). And, even if the clock tree has been designed very carefully, it is hard to guarantee that some flip-flops will not switch later than others under all process/voltage/temperature situations. In other words, avoiding clock skew is a tough and time-consuming job.

20 Fig. 2 shows the construction of an edge-triggered D flip-flop, the standard memory component of the vast majority of digital circuits. It consists of two latches L1, L2 that are driven from one clock C, but with an inverter I between the two latches' clock inputs. This way the latches L1, L2 are never open at the same time. This construction also means that the input data D_i is passed on to the output D_o instantly on the active clock edge. But, as
25 the latches are fast but not infinitely fast, they do have so-called set-up and hold times. During these short time intervals around the active clock edge the input data is not allowed to change. If it does, the output data of the flip-flop is not reliable. Clock skew occurs when the data of one flip-flop arrives at another flip-flop before the hold time of the second flip-flop has elapsed.

30

The invention is based on the recognition that clock skew can be avoided by using two non-overlapping clock phases $\Phi 1$, $\Phi 2$ instead of one (Fig. 3). The skew insensitivity is paid for by a reduction of the maximum clock speed. A wonderful feature of this clock strategy is that if all latches of the same clock phase do not open at the same time,

this does not influence the performance of the circuit. If we use this feature to purposely open the latches L1, L2 at different times, we can reduce the peak current that flows in the circuit after a clock transition: the switching current is distributed in time. The fact that the switching current is distributed in time means that the substrate bounce caused by the digital circuit is reduced. How much the reduction depends on the amount by which the peak current (or better: its dI/dt) is reduced.

Fig. 4 shows how the non-simultaneous switching of the latches can be accomplished: drive the clock input of one latch L from a delay circuit τ connected to another latch L of the same phase $\Phi 1$ or $\Phi 2$. The digital circuit has two structures like the one shown in Fig. 4: a first structure in which the latches L of Fig. 4 correspond to the latches L1 of Fig. 3 which are clocked by the clock signal having the clock phase $\Phi 1$, and a second structure in which the latches L of Fig. 4 correspond to the latches L2 of Fig. 3 which are clocked by the other clock signal having the other clock phase $\Phi 2$. The delay circuit τ can simply be a non-inverting buffer. An inverting buffer is smaller, but then two types of latches are needed for each clock phase: active-high and active-low. If the clock inputs of all latches of a circuit having many latches are placed in series like this, the end result will be an extremely slow circuit. So, a compromise has to be found between using one buffer to clock all latches of the same phase in parallel and using as many buffers as there are latches to clock them all in series.

The solution for this is to use a clock line for both clock phases (Fig. 5), in which each node of the clock line drives a number of latches. The number of latches driven by each node in the line is simply N/M , with N being the total number of latches of one clock phase and M being the number of nodes in the clock line. N is determined by the design. M must be chosen such that the clock transient is spread out over the whole clock cycle (in worst case conditions).

To keep the speed of the circuit as high as possible, the latches at inputs of the longest path of the logic should be clocked with the first buffer of the $\Phi 2$ clock line. The output of the longest path should be clocked with the last buffer in the $\Phi 1$ clock line.

In Fig. 3, $\Phi 1$ and $\Phi 2$ are drawn as signals with 25% duty cycle and evenly spaced with respect to one another. But, as there is no logic path between the two latches that make up one flip-flop, $\Phi 2$ may start immediately after $\Phi 1$ closes its last latch. In other words:

the clock generator should make $\Phi 2$ using the output of the last buffer in the $\Phi 1$ clock line as its timing reference.

A preferred embodiment of the present invention can be summarized as follows. A clock strategy is provided for digital circuits inside mixed-signal ICs. An integrated circuit in accordance with the present invention comprises a plurality of pairs of latches L1, L2 being respectively clocked by two non-overlapping clock signals $\Phi 1$, $\Phi 2$. The clock strategy is aimed at keeping the substrate bounce caused by the digital circuits as low as possible. Preferably, not all latches are clocked at the same time, but delays are inserted in the clock line so that the various latches do not consume current all at the same time. The invention relaxes the demands on the substrate sensitivity of the analog circuits.

The present invention offers the following advantages over the prior art: low substrate bounce, no clock skew, and a design approach that is identical to design approach of "normal" synchronous circuits, i.e. all 'mainstream' design tools can be used. At the end of the design process the flip-flops are replaced by double latches and clock lines. The clock control block (used in synchronous digital ICs to prevent clock skew and enter test modes) does not have to take the direction of data flow with respect to the clock into account. The lower substrate bounce can be used to reduce on-chip decoupling. Advantageously, the measure of the present invention does not necessitate a circuit to contain more flip-flops than prior art circuits to obtain a current-pulse-spreading in time. Also, the clock lines do not need to contain more inverters than the prior art clock tree. The advantages of the present invention can thus be obtained without a need for additional circuitry.

It should be noted that the above-mentioned embodiments illustrate rather than limit the invention, and that those skilled in the art will be able to design many alternative embodiments without departing from the scope of the appended claims. The clock signals $\Phi 1$, $\Phi 2$ do not need to have the same duty cycle. In the claims, any reference signs placed between parentheses shall not be construed as limiting the claim. The word "comprising" does not exclude the presence of elements or steps other than those listed in a claim. The word "a" or "an" preceding an element does not exclude the presence of a plurality of such elements. In the device claim enumerating several means, several of these means can be embodied by one and the same item of hardware. The mere fact that certain measures are recited in mutually different dependent claims does not indicate that a combination of these measures cannot be used to advantage.

CLAIMS:

1. A integrated circuit comprising:
a plurality of pairs of latches (L1, L2) being respectively clocked by two non-overlapping clock signals ($\Phi 1$, $\Phi 2$).
- 5 2. A integrated circuit as claimed in claim 1, wherein delay circuits (τ) are placed between clock inputs of latches (L) of a same clock phase ($\Phi 1$ or $\Phi 2$).
3. A integrated circuit as claimed in claim 2, wherein each delay circuit (B) drives more than one latch.

1/2




FIG. 1




FIG. 2

2/2




FIG. 3




FIG. 4




FIG. 5

INTERNATIONAL SEARCH REPORT

PCT/IB 03/00282

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 H03K19/003 H03K3/037 H03K5/15 G06F1/10

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H03K G06F

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data, PAJ, IBM-TDB

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5 229 657 A (RACKLEY DAVID T) 20 July 1993 (1993-07-20) column 3, line 66 -column 4, line 2; figures 1,4,5A column 6, line 65 -column 7, line 42	1-3
X	EP 0 712 209 A (BROOKTREE CORP) 15 May 1996 (1996-05-15) column 8, line 56 -column 9, line 28; figure 10	1,2
Y	---	3
Y	EP 0 903 660 A (LSI LOGIC CORP) 24 March 1999 (1999-03-24) column 15, line 29-46; figure 11 ---	3
	--- -/--	

☒ Further documents are listed in the continuation of box C.☒ Patent family members are listed in annex.

* Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
- *Z* document member of the same patent family

Date of the actual completion of the international search

13 May 2003

Date of mailing of the international search report

20/05/2003

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Moll, P

INTERNATIONAL SEARCH REPORT

PCT/IB 03/00282

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT		
Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5 259 006 A (PRICE RODERICK A ET AL) 2 November 1993 (1993-11-02) column 6, line 1-68; figure 4 ---	1,2
X	US 5 717 729 A (WATSON JR RICHARD B ET AL) 10 February 1998 (1998-02-10) column 8, line 45 -column 9, line 21; figure 6A ---	1,2
X	EP 0 924 859 A (ADVANCED MICRO DEVICES INC) 23 June 1999 (1999-06-23) column 3, line 39 -column 5, line 57; figure 1 ---	1,2
X	PATENT ABSTRACTS OF JAPAN vol. 010, no. 032 (E-379), 7 February 1986 (1986-02-07) -& JP 60 190020 A (HITACHI SEISAKUSHO KK;OTHERS: 01), 27 September 1985 (1985-09-27) abstract; figure 2 ---	1,2
X	US 6 205 191 B1 (DILLON JOHN B ET AL) 20 March 2001 (2001-03-20) column 9, line 32-65; figure 6A ---	1,2
X	US 5 229 668 A (HUGHES JR THOMAS A ET AL) 20 July 1993 (1993-07-20) column 3, line 40 -column 2, line 27; figures 1,6 column 7, line 29-64 ---	1,2
X	EP 0 429 728 A (IBM) 5 June 1991 (1991-06-05) column 3, line 35 -column 4, line 34; figure 2 ---	1
X	US 5 498 983 A (SCHOELLKOPF JEAN-PIERRE) 12 March 1996 (1996-03-12) column 2, line 7-20; figures 2,5 column 4, line 9--40 ---	1
X	US 6 316 979 B1 (KEETH BRENT) 13 November 2001 (2001-11-13) column 6, line 4-30; figures 7,8 ---	1
X	US 4 661 922 A (THIERBACH MARK E) 28 April 1987 (1987-04-28) column 5, line 32-68; figures 1,2 -----	1

INTERNATIONAL SEARCH REPORT

Information on patent family members

PCT/IB 03/00282

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 5229657	A	20-07-1993	NONE	
EP 0712209	A	15-05-1996	US 5596284 A CA 2162312 A1 EP 0712209 A2 JP 8237100 A US 5764074 A	21-01-1997 11-05-1996 15-05-1996 13-09-1996 09-06-1998
EP 0903660	A	24-03-1999	EP 0903660 A1 JP 11194850 A	24-03-1999 21-07-1999
US 5259006	A	02-11-1993	EP 0453171 A2 JP 4227576 A	23-10-1991 17-08-1992
US 5717729	A	10-02-1998	NONE	
EP 0924859	A	23-06-1999	US 6064232 A EP 0924859 A1 JP 11185492 A	16-05-2000 23-06-1999 09-07-1999
JP 60190020	A	27-09-1985	NONE	
US 6205191	B1	20-03-2001	AU 8387098 A TW 399368 B WO 9904528 A1	10-02-1999 21-07-2000 28-01-1999
US 5229668	A	20-07-1993	NONE	
EP 0429728	A	05-06-1991	EP 0429728 A1 DE 68916249 D1 DE 68916249 T2 JP 2029709 C JP 3181099 A JP 7066341 B US 5157286 A	05-06-1991 21-07-1994 24-05-1995 19-03-1996 07-08-1991 19-07-1995 20-10-1992
US 5498983	A	12-03-1996	FR 2711286 A1 DE 69407529 D1 DE 69407529 T2 EP 0648017 A1 JP 2657363 B2 JP 7181234 A	21-04-1995 05-02-1998 04-06-1998 12-04-1995 24-09-1997 21-07-1995
US 6316979	B1	13-11-2001	US 6111446 A	29-08-2000
US 4661922	A	28-04-1987	CA 1232034 A1 EP 0128195 A1 GB 2131193 A ,B GB 2131993 A ,B JP 60500038 T WO 8402433 A1	26-01-1988 19-12-1984 13-06-1984 27-06-1984 10-01-1985 21-06-1984